This is an electronic reprint of the original article.
This reprint may differ from the original in pagination and typographic detail.

Averin, D.; Möttönen, M.; Pekola, J.P.
Maxwell's demon based on a single-electron pump

Published in:
Physical Review B

DOI:
[10.1103/PhysRevB.84.245448](https://doi.org/10.1103/PhysRevB.84.245448)

Published: 27/12/2011

Document Version
Publisher's PDF, also known as Version of record

Please cite the original version:
Averin, D., Möttönen, M., & Pekola, J. P. (2011). Maxwell's demon based on a single-electron pump. *Physical Review B*, 84(24), 1-5. [245448]. <https://doi.org/10.1103/PhysRevB.84.245448>

This material is protected by copyright and other intellectual property rights, and duplication or sale of all or part of any of the repository collections is not permitted, except that material may be duplicated by you for your research use or educational purposes in electronic or print form. You must obtain permission for any other use. Electronic or print copies may not be offered, whether for sale or otherwise to anyone who is not an authorised user.

Maxwell's demon based on a single-electron pump

Dmitri V. Averin,¹ Mikko Möttönen,^{2,3} and Jukka P. Pekola²

¹*Department of Physics and Astronomy, Stony Brook University, SUNY, Stony Brook, New York 11794-3800, USA*

²*Low Temperature Laboratory, Aalto University, P.O. Box 13500, FIN-00076 Aalto, Finland*

³*Department of Applied Physics/COMP, Aalto University, P.O. Box 14100, FIN-00076 Aalto, Finland*

(Received 27 August 2011; published 27 December 2011)

We propose and analyze a possible implementation of Maxwell's demon (MD) based on a single-electron pump. It presents a practical realization of MD in a solid-state environment. We show that measurements of the charge states of the pump and feedback control of the gate voltages lead to a net flow of electrons against the bias voltage ideally with no work done on the system by the gate control. The information obtained in the measurements converts thermal fluctuations into energy stored in a capacitor. We derive the conditions on the detector back action and measurement time necessary for implementing this conversion.

DOI: [10.1103/PhysRevB.84.245448](https://doi.org/10.1103/PhysRevB.84.245448)

PACS number(s): 05.30.-d, 05.40.-a, 73.23.Hk, 74.78.Na

I. INTRODUCTION

Work, heat, and reversibility are topics of intense current interest in driven small systems, where fluctuations play an important role. Instead of familiar inequalities of macroscopic thermodynamic quantities, equalities have been formulated to describe ensemble averages of work and free-energy-related quantities even in far-from-equilibrium situations.¹⁻³ Moreover, it has been demonstrated that in certain systems, it is possible to realize experimentally Maxwell's demon,⁴ the process in which the information of an observer is used to convert the energy of thermal fluctuations into free energy without performing work on the system.⁵⁻⁸ Qualitatively, such a conversion inverts the information-energy relation in the Landauer principle⁹ which equates the erasure of information to generation of heat.

Single-electron tunneling (SET) devices which manipulate individual electrons in structures of metallic tunnel junctions¹⁰ have several general advantages for studying nanoscale thermodynamics. These include the simplicity of the basic dynamics which is understood theoretically to a very good precision, a large degree of experimental control that allows one to design and implement various possible structures, and a close connection to practical information processing. In this paper, we demonstrate that a single-electron pump, monitored by a charge detector which can resolve individual electrons, can be adapted to act as Maxwell's demon, i.e., an information-to-energy converter. We show that in the limit of infinitely fast and error-free detection, the pump can become an ideal energy extractor. This limit can be approached experimentally by lowering the electron tunneling rates in the pump, e.g., by employing hybrid normal-metal-insulator-superconductor (NIS) junctions.¹¹

Away from the ideal limit, the rate and efficiency, with which such an SET demon extracts free energy from thermal fluctuations, depend critically on the detector characteristics: they include the measurement time which is determined by the detector sensitivity and its output noise and defines the information acquisition rate, and the back-action noise of the detector which should be sufficiently weak to ensure that the demon utilizes only the energy of the thermal fluctuations. The quantitative limitations on the detector obtained below for the demon operation are less stringent than for the quantum-

limited detection, the fact that makes realistic the prospect of experimental realization of Maxwell's demon in the SET configuration.

II. SINGLE-ELECTRON PUMP

The physical system we consider is the three-junction single-electron pump¹¹ shown in Fig. 1. Here, three tunnel junctions define the internal islands of the structure. Each junction has a tunnel resistance R_T and capacitance C , and the circuit is controlled by gate voltages V_{gi} on the capacitance C_g , at islands $i = 1, 2$. The main part of our discussion is independent of whether the junction electrodes are normal or superconducting. In particular, as shown below, the pump that is most promising for experimental demonstration of the demon should be based on the NIS junctions. The pump is biased by the voltage V . Although the precise nature of the voltage source is not important, to be specific, we adopt the model of the source as a large capacitor $C_0 \gg C, C_g$ with a large charge eN on it, creating the voltage $V = eN/C_0$ across the pump, where e is the electron charge. We consider the limit $C_0, N \rightarrow \infty$, when the voltage V is independent of the number of electrons n transferred through the pump and the numbers n_i of electrons on the islands $i = 1, 2$.

The pump operation requires the gate voltages V_{gi} to be time dependent. This makes it convenient to separate the electrostatic energy U of the system into the gate-voltage-independent part U_0 which includes the usual bare charging energy of the pump capacitors and the energy of the charges n, n_1, n_2 due to the voltage V , and the gate-voltage-dependent bias energy U_g , so that $U = U_0 + U_g$. In the assumed regime of small gate capacitances, $C \gg C_g$, we have

$$U_0 = E_C(n_1^2 + n_2^2 + n_1 n_2) - eV(n_1 + 2n_2 + 3n)/3, \quad (1)$$

$$U_g = -E_C[n_1(2n_{g1} + n_{g2}) + n_2(n_{g1} + 2n_{g2})], \quad (2)$$

where $E_C \equiv e^2/3C$ and $n_{gi} \equiv C_g V_{gi}/e$.

Below, we focus on the low-temperature regime, $k_B T \ll E_C$, and gate voltage range such that only three possible charge states on the islands, $(n_1, n_2) = (0, 0), (1, 0), (0, 1)$, can be

FIG. 1. Three-junction electron pump biased by the voltage V that is created by charge eN , $N \gg 1$, on a large capacitor C_0 . The time-dependent gate voltages V_{g1}, V_{g2} can move electrons even against the bias from right to left. The number n counts the electrons transferred through the pump. Electron numbers n_1, n_2 on the internal islands of the pump can be monitored by a charge detector (not shown) with subelectron resolution, e.g., by a single-electron transistor.

occupied in practice. The possible changes of the electrostatic energy U in the electron transitions are given then by

$$\begin{aligned} \Delta U_{1,\pm} &= \pm E_C(1 - 2n_{g1} - n_{g2}) \mp eV/3, \\ \Delta U_{2,\pm} &= \pm E_C(n_{g1} - n_{g2}) \mp eV/3, \\ \Delta U_{3,\pm} &= \pm E_C(n_{g1} + 2n_{g2} - 1) \mp eV/3. \end{aligned} \quad (3)$$

Here, the subscript $k, \pm$ refers to tunneling between the three charge states through the k th junction from the left end in Fig. 1, with $\pm$ indicating its direction: $+$ to the right, $-$ to the left. The conditions $\Delta U_{k,\pm} = 0$ determine the borders of stability of the charge states shown in Fig. 2:

$$\begin{aligned} (0,0) - (1,0) : n_{g2} + 2n_{g1} &= 1 - eV/3E_C, \\ (1,0) - (0,1) : n_{g2} - n_{g1} &= -eV/3E_C, \\ (0,1) - (0,0) : 2n_{g2} + n_{g1} &= 1 + eV/3E_C. \end{aligned} \quad (4)$$

FIG. 2. Stability diagram of the pump, and the demon operation cycle. The black solid lines crossing at $n_{g1} = n_{g2} = 1/3$ separate the stable charge configurations $(0,0)$, $(1,0)$, and $(0,1)$ of the pump at $V = 0$. The dashed lines that form a triangle encircling $n_{g1} = n_{g2} = 1/3$ are the corresponding borders for $V = 0.3E_C$. Inside this triangle there are no stable charge states, and current runs along the bias. The arrows indicate a possible trajectory of the demon operation which converts information into free energy.

For $V = 0$, these borders intersect at the triple point $(n_{g1}, n_{g2}) = (1/3, 1/3)$, where all three states have the same energy, or they form a triangle around this point for $V \neq 0$; see Fig. 2. The standard pumping is obtained¹² by changing the gate voltages adiabatically along a trajectory that encircles this triangle.

III. THERMODYNAMICS OF THE PUMP

Thermodynamic properties of the pump follow from the remark that the energy changes $\Delta U_{k,\pm}$ in Eq. (3) give directly the amount of heat $Q_{k,\pm}$ dissipated in the electrodes in each electron transition,⁷ $Q_{k,\pm} = -\Delta U_{k,\pm}$. (The sign change accounts for the natural convention that decreasing energy generates positive heat.) Summing these changes over all electron transitions and adding the change of energy U between the transition due to the time evolution of U_g [Eq. (2)], we obtain the total change ΔU over some trajectory of the pump dynamics as

$$\Delta U = -Q - E_C \int [(2n_1 + n_2)dn_{g1}(t) + (n_1 + 2n_2)dn_{g2}(t)], \quad (5)$$

where Q is the total heat generated in the evolution. Subtracting the total change ΔU_g from both sides of this equation, we obtain the first-law-of-thermodynamics relation for the pump:

$$\Delta U_0 = -Q + E_C \int [(2n_{g1} + n_{g2})dn_1(t) + (n_{g1} + 2n_{g2})dn_2(t)]. \quad (6)$$

Here, the second term on the right coincides with the regular expression for the electrostatic work W done by the changing gate voltages. Similarly, the second term in Eq. (5) is sometimes used to define the thermodynamic work¹³ convenient in the discussions of the nonequilibrium fluctuation relations.^{2,3} Since the charges n_i change by discrete jumps, the work W in Eq. (6) reduces to the sum over the times t_j of these jumps:

$$W = E_C \sum_j [(2n_{g1} + n_{g2})\delta n_1 + (n_{g1} + 2n_{g2})\delta n_2]_{t=t_j}, \quad (7)$$

where $\delta n_i = \pm 1$ refer to the changes of n_i at the time t_j .

We will mostly consider closed cycles of pump evolution, when the gate charges n_{gi} and the island charges n_i return to their initial values at the end of the cycle, and the only overall change is in the number n of transferred electrons: $\delta n = \pm 1$ for the elementary cycle, depending on the pumping direction, which gives $\Delta U_0 = \pm eV$ from Eq. (1). Since $k_B T \ll E_C$, we may consider only the cycles that start and end in one certain charge configuration, so that the entropy in the charge degree of freedom of the pump vanishes, and the free energy F coincides with the internal energy U_0 yielding $\Delta F = \Delta U_0$. Using Eq. (6) we get for pumping against the bias

$$W = \Delta U_0 + Q = eV + Q, \quad (8)$$

i.e., the work done by the gates in one cycle is partly dissipated into heat and partly increases the free energy of the pump by charging the capacitor C_0 .

IV. ADIABATIC ELECTRON PUMPING

As an application of Eq. (8), we first consider the usual slow pumping, for which there is no need to extract information on the system. Because of the randomness of the tunneling events, the heat Q , and therefore the work done by the gates, fluctuate from cycle to cycle. The statistics of Q and W over the cycles can be determined from the statistics of dissipated heat in the individual SET transitions from one charge state to the next in the cycle. Quantitatively, this statistics depends on the electron tunneling rates $\Gamma_{k,\pm}$ for the transitions between the charge states in Eq. (3), which, in the case of the pump made of normal-metal conductors with a constant density of states, are given by the standard expression $\Gamma = (e^2 R_T)^{-1} \Delta U / [e^{\Delta U / (k_B T)} - 1]$.

In the limit of a slow evolution, the distribution of heat in the individual SET transitions in this case is known to be Gaussian.⁷ The sum of the Gaussian distributions in the three transitions of one cycle results in the Gaussian distribution of the total heat Q , with the average $\langle Q \rangle$ and the width σ_Q of the distribution related in the same way as for the individual transitions, $\sigma_Q^2 = 2k_B T \langle Q \rangle$.⁷ The average $\langle Q \rangle$ depends on the rates η_k of the change of energies $\Delta U_{k,\pm}$ in Eq. (3) at the time when the gate voltage trajectory crosses the border between the charge states corresponding to the transition in the k th junction (Fig. 2): $\langle Q \rangle \simeq 0.43(e^2 R_T / k_B T) \sum |\eta_k|$. For instance, in a typical case of harmonic variation of gate voltages with frequency ω and amplitude V_g , we have $n_{g1}(t) = 1/3 + (C_g V_g / e) \cos(\omega t)$, $n_{g2}(t) = 1/3 - (C_g V_g / e) \sin(\omega t)$, and for $eV \ll E_C$,

$$\langle Q \rangle \simeq 2.51(eV_g E_C / k_B T) C_g R_T \omega.$$

Thus, for $\omega \rightarrow 0$, the generated heat vanishes in every pumping cycle, and $W = eV$, i.e., the work done by the gates on the tunneling electrons to pump them against the bias equals the change in free energy.

V. DEMON PUMPING

Let us consider next the demon-type operation, in which electrons flow against the bias with no net work done by the gate voltages, $W = 0$. As follows from Eq. (8), in this regime, $\Delta F = eV = -Q$, i.e., $Q < 0$, and the energy is extracted from thermal fluctuations. This is achieved by a detector that can observe transitions in the pump.

A possible operation cycle of the demon is described on the stability diagram in Fig. 2 by the triangle of arrows. First, set $n_{g1} = 0, n_{g2} = 1/2$, i.e., the degeneracy point at $V = 0$ for the charge states $(0,0)$ and $(0,1)$, and take $(0,0)$ to be the initial state of the cycle. Comparison of the two energy differences in Eq. (3) at these gate voltages, $\Delta U_{1,+} = E_C/2 - eV/3$ and $\Delta U_{3,-} = eV/3$, shows that for $E_C \gg 4eV/3 \sim k_B T$ the system will make with dominant probability a fluctuation-induced transition into the state $(0,1)$ (against the bias) and not to $(1,0)$ (along the bias). As soon as the transition to $(0,1)$ occurs, the detector registers it and the gate voltages shift

quickly to the position $n_{g1} = n_{g2} = 1/2$. Similar arguments as above show that at these values of the gate voltages, with dominant probability, the system makes the transition to state $(1,0)$. Once the transition is observed, the gates are moved quickly to $n_{g1} = 1/2, n_{g2} = 0$, and when the next dominant transition to $(0,0)$ occurs and is registered, the gates move back to the initial positions $n_{g1} = 0, n_{g2} = 1/2$, completing the cycle.

Equation (7) can be used to show that the total work done in this process vanishes, $W = 0$. (The work in the first and last transitions sum up to zero and vanishes for the middle transition.) However, the tunneling electron charges the capacitor C_0 , increasing the free energy of the pump by $\Delta F = eV$ in the closed cycle with the energy coming from thermal fluctuations, $Q = -eV < 0$. The average generated power by the demon is $P = (eV/3)\Gamma(eV/3)$. As usual for general Maxwell's demon operation,⁴ this generation of power directly from thermal fluctuations does not violate the second law of thermodynamics because of the entropy produced by the information erasure in the detector.

In this first discussion of the SET implementation of Maxwell's demon, we focus on the thermodynamic processes in the pump itself, without taking into account the energy dissipation in the control and measurement circuits. Development of the reversible versions of these circuits which dissipate the thermodynamical minimum of energy represent a separate future line of research.

VI. DETECTION SPEED AND BACK ACTION

Even without the question of energy dissipation in the measurement and feedback control circuits, they represent the central element of the demon operation described above. On one hand, the measurement and feedback control sequence needs to be much faster than the electron tunneling rates. On the other hand, the back action of the detector to the system has to be low enough.

The typical charge detectors used in mesoscopic structures, like the SET pump here, are based on either the SET transistors¹⁰ or quantum point contacts.¹⁴ Both types of detectors convert the input charge signal q of a subelectron magnitude into the output signal of the dc current I , effectively amplifying the input. For weak detector coupling to the pump, the conversion process is linear and can be characterized by the linear-response coefficient $\lambda = \partial I / \partial q$. General statistical mechanics of the detectors shows that the measurement is unavoidably accompanied by the output current noise with some spectral density S_I and the back-action noise S_V of the potential of the island coupled to the detector, since the spectral densities are limited from below by what is effectively the Heisenberg uncertainty relation, $S_I S_V \geq (\hbar \lambda / 4\pi)^2$ (see, e.g., Ref. 15). Both spectral densities are constant below a cutoff frequency ω_C of the classical part of the noise.

We focus the subsequent discussion on the case of SET electrometers, although qualitatively, the same considerations apply to measurements by quantum point contacts. The charges on the two islands should be either monitored by two independent detectors or by a single detector coupled asymmetrically to both islands. Here, the individual detector

parameters can be different, but the equations below still apply to the detection process of each individual transition.

The main effect of the back-action noise S_V of the potential is the transfer of energy to electrons tunneling in the pump, stimulating the tunneling rate. Quantitatively, this effect can be described as decoherence of the voltage drop across the tunnel junction. The white noise S_V produces the simplest exponential decoherence with the rate $\gamma' = \pi e^2 S_V / \hbar^2$. In the usual description of the rate Γ of electron tunneling between two normal-metal electrodes, this decoherence gives the Lorentzian line shape of the tunneling:

$$\Gamma = \frac{1}{e^2 R_T} \int d\epsilon_i d\epsilon_f f(\epsilon_i) [1 - f(\epsilon_f)] \times \frac{\gamma/\pi}{(\epsilon_i - \epsilon_f - \Delta U)^2 + \gamma^2},$$

where $f(\epsilon)$ is the Fermi distribution of electrons in the electrodes, and $\gamma \equiv \hbar \gamma'$. In operating Maxwell's demon, one would be interested in extracting energy from thermal fluctuations, and not from the detector noise. Thus it is important to keep the effects of noise small. For small but finite γ , evaluating the tunneling rate, one obtains $\Gamma = \frac{1}{e^2 R_T} [\frac{\Delta U}{\exp[\Delta U/(k_B T)] - 1} + \frac{\gamma}{\pi} \ln(\hbar \omega_C / k_B T)]$, where the second term represents the detector-induced correction with a logarithmic accuracy in the large frequency ω_C . For the SET detector, this frequency is roughly given by the bias voltage V_D across the transistor, $\omega_C \simeq e V_D / \hbar$. The condition that this correction is small for $\Delta U \sim k_B T$ (regime of the demon operation) imposes constraint on S_V :

$$S_V \ll \hbar k_B T / [e^2 \ln(\hbar \omega_C / k_B T)]. \quad (9)$$

The cutoff frequency $1/\tau$ of the output detector noise S_I is typically much smaller than the intrinsic cutoff ω_C because of the finite bandwidth of the information carrying wiring. For instance, a standard dc coupled SET electrometer has a bandwidth of about 1 kHz.¹¹ (In principle, it can be improved to the megahertz range with an rf-SET electrometer.¹⁶) Together with S_I , the cutoff $1/\tau$ determines the accuracy of the detection of the measured charge state. Assuming the usual Lorentzian line shape of the spectrum, $S_I(\omega) = S_I(0)/[1 + (\omega\tau)^2]$, we estimate the magnitude of the output current noise as $\sigma \equiv \langle \tilde{I}^2 \rangle = \pi S_I(0)/\tau$. Distinguishing the two values of the output current that correspond to the two charge states, an electron on or off the island, that differ by $\Delta I = e\lambda$, in the presence of this noise can be achieved only with a finite probability p of a mistake. The output current noise is produced by many tunneling electrons in the transistor and is therefore Gaussian. This implies that $p = (1/2)\text{erfc}(\Delta I/\sqrt{8\sigma}) \simeq (\sqrt{2\sigma/\pi}/\Delta I)e^{-(\Delta I)^2/8\sigma}$. The condition that mistakes in the charge detection are negligible imposes the following constraint:

$$S_I/\lambda^2 \ll e^2 \tau / 8\pi. \quad (10)$$

Since the detector makes the choice of two options, an electron on or off the island, the amount of usable information obtained in measurement of each transition is roughly given by $\ln 2$, while the energy extracted is $eV/3 \simeq k_B T$. We see that the SET demon has qualitatively the same information-

energy relation as in the standard Landauer principle,⁹ with one bit of information corresponding roughly to $k_B T$ of energy gain. We note again that, as briefly mentioned above, the discussed practical detector itself dissipates much more energy than the energy gained in the demon operation process; however, this energy is dissipated outside the pump.

VII. PHYSICAL REALIZATION OF THE PUMP

If the condition (10) is satisfied, the time required to detect the change in the charge state of the pump is given directly by τ . The operation of Maxwell's demon described above assumed that electron transition is detected, and the gate voltages are changed before the electron has a chance to tunnel back, i.e., $\Gamma \ll \tau^{-1}$, where Γ is the rate of such reverse tunneling. This tunneling is driven by the energy change $eV/3$, so that $\Gamma \sim V/(eR_T)$ for the normal-metal pump. The conditions (9), (10), and $\Gamma \ll \tau^{-1}$ are compatible with the Heisenberg relation for detectors, $S_I S_V / \lambda^2 \geq (\hbar/4\pi)^2$, provided that $\hbar \Gamma \ll k_B T$, and thus they can be satisfied with the detector far from being quantum limited (which satisfies Heisenberg relation as an equality). Practical limitations on the detector bandwidth, however, imply that these conditions cannot be satisfied with usual normal-metal pumps.

Typically $E_C/e \gg 100 \mu\text{V}$, and in order to exploit this available energy, one would like to set $V \sim 100 \mu\text{V}$, which would be reasonably larger than $k_B T$ at the typical working temperature of about 100 mK for such a device. Even if the detector is fast, $\tau \sim 1 \mu\text{s}$, to satisfy condition $\Gamma \ll \tau^{-1}$ we need to have $R_T \gg V\tau/e \sim 1 \text{ G}\Omega$, which is impractically large. This problem can be resolved by employing superconducting and normal-metal electrodes at each junction of the pump, i.e., creating NIS junctions.¹¹ In this case,¹⁷ the rates at $eV/3 \ll \Delta$, where Δ is the superconducting gap, are suppressed exponentially from those of the normal state junctions, and it is easy to satisfy $\Gamma \ll \tau^{-1}$ with $R_T \sim 1 \text{ M}\Omega$, e.g., at the temperature of 100 mK.¹⁸ The condition on the negligible back action is also satisfied more easily in this case by making $\hbar \omega_C \ll \Delta$, so that the back-action noise does not excite tunneling. Simple estimates of λ and S_I for the SET transistor show that Eq. (10) can also be satisfied by taking the tunneling rates Γ_D in it and its coupling capacitance C_0 to the pump such that $\Gamma_D \tau (C_0/C)^2 \gg 8\pi$. With the discussed pump parameters, the power generated by the demon is limited to $P \lesssim 10 \text{ aW}$, and is hardly observable directly, but only indirectly by measuring the collected charge at the bias capacitor C_0 .

VIII. CONCLUSIONS

In conclusion, we have designed a practical scheme to realize Maxwell's demon based on a single-electron pump and charge detectors. We derived conditions that the pump and detectors should satisfy for the demon operation. The pumps based on the NIS junctions, i.e., with superconducting and normal-metal electrodes at each junction, seem to provide an experimentally feasible device to satisfy these conditions.

ACKNOWLEDGMENTS

The authors acknowledge Academy of Finland, IARPA, Emil Aaltonen Foundation, European Community's Seventh

Framework Programme under Grant Agreement No. 238345 (GEOMDISS), and European Research Council under Grant Agreement No. 278117 (SINGLEOUT) for financial support.

-
- ¹G. N. Bochkov and Yu. E. Kuzovlev, *Physica A* **106**, 443 (1981).
²C. Jarzynski, *Phys. Rev. Lett.* **78**, 2690 (1997).
³G. E. Crooks, *Phys. Rev. E* **60**, 2721 (1999).
⁴*Maxwell's Demon 2*, edited by H. S. Leff and A. F. Rex (IOP, Bristol, 2003).
⁵K. Maruyama, F. Nori, and V. Vedral, *Rev. Mod. Phys.* **81**, 1 (2009).
⁶S. Toyabe, T. Sagawa, M. Ueda, E. Muneyuki, and M. Sano, *Nat. Phys.* **6**, 988 (2010).
⁷D. V. Averin and J. P. Pekola, *Europhys. Lett.* **96**, 67004 (2011).
⁸G. Schaller, C. Emary, G. Kiesslich, and T. Brandes, *Phys. Rev. B* **84**, 085418 (2011).
⁹R. Landauer, *IBM J. Res. Devel.* **3**, 183 (1961).
¹⁰D. V. Averin and K. K. Likharev, *J. Low Temp. Phys.* **62**, 345 (1986).
¹¹V. F. Maisi, O.-P. Saira, Yu. A. Pashkin, J. S. Tsai, D. V. Averin, and J. P. Pekola, *Phys. Rev. Lett.* **106**, 217003 (2011).
¹²H. Pothier, P. Lafarge, C. Urbina, D. Esteve, and M. H. Devoret, *Europhys. Lett.* **17**, 249 (1992).
¹³C. Jarzynski, *C. R. Physique* **8**, 495 (2007).
¹⁴M. Field, C. G. Smith, M. Pepper, D. A. Ritchie, J. E. F. Frost, G. A. C. Jones, and D. G. Hasko, *Phys. Rev. Lett.* **70**, 1311 (1993).
¹⁵D. V. Averin, in *Quantum Noise in Mesoscopic Physics*, edited by Yu. V. Nazarov (Kluwer, Dordrecht, 2003), p. 229; e-print [arXiv:cond-mat/0301524v1](https://arxiv.org/abs/cond-mat/0301524v1).
¹⁶R. J. Schoelkopf, P. Wahlgren, A. A. Kozhevnikov, P. Delsing, and D. E. Prober, *Science* **280**, 1238 (1998).
¹⁷J. P. Pekola, J. J. Vartiainen, M. Möttönen, O.-P. Saira, M. Meschke, and D. V. Averin, *Nat. Phys.* **4**, 120 (2008).
¹⁸O.-P. Saira, M. Möttönen, V. F. Maisi, and J. P. Pekola, *Phys. Rev. B* **82**, 155443 (2010).